

2-22-00

PTO/SB/05 (4/98)

Please type a plus sign (+) inside this box → ☐Approved for use through 09/30/2000. OMB 0651-0032
Patent and Trademark Office: U.S. DEPARTMENT OF COMMERCE

Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it displays a valid OMB control number.

**UTILITY
PATENT APPLICATION
TRANSMITTAL**

(Only for new nonprovisional applications under 37 C.F.R. § 1.53(b))

Attorney Docket No. 11-1045

First Inventor or Application Identifier Richard L. Davis

Title HYBRID COHERENT-OPTICAL, RF SIGNAL CHANNELIZER

Express Mail Label No. EK275571846US

APPLICATION ELEMENTS

See MPEP chapter 600 concerning utility patent application contents.

1. ☒ * Fee Transmittal Form (e.g., PTO/SB/17)
(Submit an original and a duplicate for fee processing)
2. ☒ Specification [Total Pages 11]
(preferred arrangement set forth below)
- Descriptive title of the invention
 - Cross References to Related Applications
 - Statement Regarding Fed sponsored R & D
 - Reference to Microfiche Appendix
 - Background of the invention
 - Brief Summary of the invention
 - Brief Description of the Drawings (if filed)
 - Detailed Description
 - Claim(s)
 - Abstract of the Disclosure
3. ☒ Drawing(s) (35 U.S.C. 113) [Total Sheets 2]
4. Oath or Declaration [Total Pages 2]
- a. ☒ Newly executed (original or copy)
 - b. ☐ Copy from a prior application (37 C.F.R. § 1.63(d))
(for continuation/divisional with Box 16 completed)
 - i. ☐ DELETION OF INVENTOR(S)
Signed statement attached deleting
inventor(s) named in the prior application,
see 37 C.F.R. §§ 1.63(d)(2) and 1.33(b).

**NOTE FOR ITEMS 1 & 13 IN ORDER TO BE ENTITLED TO PAY SMALL ENTITY
FEES, A SMALL ENTITY STATEMENT IS REQUIRED (37 C.F.R. § 1.27), EXCEPT
IF ONE FILED IN A PRIOR APPLICATION IS RELIED UPON (37 C.F.R. § 1.28).**

ADDRESS TO:Assistant Commissioner for Patents
Box Patent Application
Washington, DC 20231

5. ☐ Microfiche Computer Program (Appendix)
6. Nucleotide and/or Amino Acid Sequence Submission
(if applicable, all necessary)
- a. ☐ Computer Readable Copy
 - b. ☐ Paper Copy (identical to computer copy)
 - c. ☐ Statement verifying identity of above copies

ACCOMPANYING APPLICATION PARTS

7. ☒ Assignment Papers (cover sheet & document(s))
8. ☒ 37 C.F.R. § 3.73(b) Statement (when there is an assignee) ☒ Power of Attorney
9. ☐ English Translation Document (if applicable)
10. ☒ Information Disclosure Statement (IDS)/PTO-1449 ☒ Copies of IDS Citations
11. ☐ Preliminary Amendment
12. ☒ Return Receipt Postcard (MPEP 503)
(Should be specifically itemized)
13. ☐ * Small Entity Statement(s) ☐ Statement filed in prior application
(PTO/SB/09-12) Status still proper and desired
14. ☐ Certified Copy of Priority Document(s)
(if foreign priority is claimed)
15. ☐ Other: _____

16. If a CONTINUING APPLICATION, check appropriate box, and supply the requisite information below and in a preliminary amendment:☐ Continuation ☐ Divisional ☐ Continuation-in-part (CIP)

of prior application No. _____ / _____

Prior application information: Examiner _____

Group / Art Unit: _____

For CONTINUATION or DIVISIONAL APPS only: The entire disclosure of the prior application, from which an oath or declaration is supplied under Box 4b, is considered a part of the disclosure of the accompanying continuation or divisional application and is hereby incorporated by reference. The incorporation can only be relied upon when a portion has been inadvertently omitted from the submitted application parts.

17. CORRESPONDENCE ADDRESS☐ Customer Number or Bar Code Label: _____or ☒ Correspondence address below

(Insert Customer No. or Attach bar code label here)

Name	Patent Counsel				
	TRW Inc.				
Address	Law Dept.				
	One Space Park, Bldg. E2/6072				
City	Redondo Beach	State	CA	Zip Code	90278
Country	U.S.A.	Telephone	(310) 812-4910	Fax	(310) 812-2687

Name (Print/Type)	Connie M. Thousand	Registration No. (Attorney/Agent)	43,191
Signature	<i>Connie Thousand</i>	Date	2-18-2000

Burden Hour Statement: This form is estimated to take 0.2 hours to complete. Time will vary depending upon the needs of the individual case. Any comments on the amount of time you are required to complete this form should be sent to the Chief Information Officer, Patent and Trademark Office, Washington, DC 20231. DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO: Assistant Commissioner for Patents, Box Patent Application, Washington, DC 20231.

CERTIFICATE OF MAILING BY "EXPRESS MAIL"

"Express Mail Mailing Label Number"

EK275571846US

Date of Deposit 02/18/00

I hereby certify that this paper or fee is being deposited with the United States Postal Service "Express Mail Post Office to Addressee" Service under 37 CFR §1.10 on the date indicated above and is addressed to the Commissioner of Patents and Trademarks, Washington, D.C. 20231.

Lorna L. Schott

(Typed or printed name of person mailing)

(Signature of person mailing)

HYBRID COHERENT-OPTICAL, RF SIGNAL CHANNELIZER

CROSS REFERENCE TO RELATED APPLICATIONS

This application is related to commonly owned co-pending patent application, Serial No. 08/759,901, filed on December 4, 1996, entitled "All Optical RF Signal Channelizer," by Wickham, et al.

5

BACKGROUND OF THE INVENTION

Field of the Invention

10

The present invention relates to an optical channelizer system and more particularly to an optical channelizer system adapted to provide RF signal channelization at frequencies in the order of 100GHz or more which instantaneously channelizes the entire signal spectrum into channels having a few megahertz.

Description of the Prior Art

Various factors are driving communications systems toward higher frequency and larger bandwidth. For example, available communications bandwidth is disappearing as the number

of users and the bandwidth per user escalates forcing communication links to higher frequencies. In addition, newer communication systems, such as military communications are increasingly being driven toward higher frequencies and larger bandwidth user requirements.

For example, modern missile seekers and imaging radar systems are utilizing frequencies
5 around 100 GHz to achieve antenna directivity and higher resolution for small aperture systems.

In order to accommodate relatively high bandwidth and high frequencies, RF communications systems are known to employ optical carrier transmission of the RF signal. Examples of such systems are disclosed in U.S. Patent No. 4, 468,766; 4,695,790; 5,005,946; 5,347,535; 5,377,035 and U.S. Statutory Invention Registration H1059.

10 Optical channelizers are used to perform spectral analysis of the newer high frequency communication signals. Such optical channelizers are known to process relatively wider bandwidth than comparable RF channelizers for real time identification of complex signals. Such optical channelizers are used in particular to channelize or divide up a relatively wide bandwidth signal into several subbands or channels. Although such optical channelizers are
15 known to process relatively wider bandwidth than known RF channelizers, many optical channelizers utilize acousto-optic technology which limits the bandwidth to a few gigahertz. Examples of optical communications systems utilizing acousto-optic technology are disclosed in U.S. Patent No. 4,448,494; 4,644,267; 5,005,946; 5,105,380; 5,327,142 and 5,363,221.

In order to resolve this problem, optical channelizers have been developed which do not
20 depend on the acousto-optic technology as disclosed in commonly owned co-pending U.S. patent application Serial No. 08/759,901 filed on December 4, 1996. In that application, as illustrated in Figs. 1 and 2, an optical channelizer, generally identified with the reference numeral 20 includes a diffraction grating. The RF signal spectrum, generally identified with

the reference numeral 22, is spatially mapped to positions across a 1xn photo-detector array 24 by the diffraction grating. A mode locked laser 26 provides a comb of optical local oscillator (LO) frequencies 28 (Fig. 2), separated by the desired channel spacing. The LO signals are optically heterodyned with the signal spectrum at the photo-detector array 24. In this way, each

5 detector generates the same band of optical frequencies so that each channel may use the same post detection electronics. The band is centered on an intermediate frequency (IF) that is determined by adjusting the offset (Fig. 1) in the incident angles at which the signal and the local oscillator lasers illuminate the grating. A complex signal spectrum (phase and amplitude) is extracted by measuring the in-phase and quadrature components of the heterodyne products.

10 Each detector is followed by a IF filter whose bandwidth is generally set to the channel spacing in order to achieve a hundred percent frequency coverage. Unfortunately, due primarily to size constraints, the optical channelizer, disclosed in the '901 patent application, is limited to minimal channel bandwidth of about 1GHz. Although it is possible to improve the channelizer sensitivity, dynamic range and resolution by reducing the bandwidth of the post detection IF

15 filter, such an approach compromises the frequency coverage. For example, a 1 GHz channelizer with 40 MHz IF only detect signals within the IF filters pass band, thus being blind to 960 MHz out of every 1 GHz of bandwidth or 96% of all possible signals. Thus, there is a need for an optical channelizer for use with signals up to 100 GHz with improved resolution.

SUMMARY OF THE INVENTION

20 The present invention relates to an optical channelizer system that is adapted to provide instantaneous RF signal channelization at frequencies on the order of 100GHz or more into channels having bandwidth as small as a few megahertz. In order to improve the channel

resolution the optical channelizer system is formed from a plurality of parallel channelizers, for example, twenty-five parallel sub channelizers which can provide 1 GHz channel spacing and 40 MHz signal resolution.

DESCRIPTION OF THE DRAWINGS

5 These and other advantages of the present invention will be relatively understood with reference to the following specification and attached drawing, wherein:

Fig. 1 is a conceptual diagram of a known optical channelizer.

Fig. 2 is a physical drawing of the optical channelizer illustrated in Fig. 1.

Fig. 3 is a physical diagram of an optical channelizer in accordance with one aspect of
10 the present invention illustrating the use of a Bragg cell for replicating the signal spectrum.

Fig. 4 is a physical diagram of the optical channelizer in accordance with illustrating the use of the present invention a monolithic optical splitter/amplifier integrated circuit (MOSAIC) for splitting the LO signals.

Fig. 5 illustrates the invention utilizing the MOSAIC as well as the Bragg cell.

15 **DETAILED DESCRIPTION OF THE INVENTION**

The present invention relates to an optical channelizer system that is adapted to provide RF signal channelization at frequencies on the order of 100 GHz or more which simultaneously channelizes the signal spectrum into channels having bandwidths as small as a few MHz. The optical channelizer system in accordance with the present invention is adapted to provide
20 improved resolution while at the same time maintaining a suitable physical size so that it is deployable on various terrestrial and airborne platforms. In particular, as illustrated in Figs. 3-5, the optical channelizer system in accordance with the present invention is formed from a

plurality of subchannelizers, arranged to operate in parallel.

Although, the system is described and illustrated for channelizing signals having a bandwidth of a 100 GHz or more, it will be understood by those of ordinary skill in the art, that the principles of the present invention are broadly applicable to signals having a bandwidth
5 more or less than a 100 GHz. An important aspect of the present invention is that the problems associated with the channelizer illustrated in Figs. 1 and 2 and discussed above are solved by dividing the signal spectrum and the local oscillator comb frequencies prior to applying those signals to an optical channelizer, such as, the optical channelizer 20, discussed above and illustrated in Figs. 1 and 2. However, it should be understood that the principles of the present
10 invention can be utilizing various types of channelizers, such as channelizers based on integrated optical arrayed wave guide gratings, for example, U. S. Patent 5, 943,452.

Referring to Fig. 3, the optical channelizer system in accordance with the present invention is generally identified with the reference numeral 32. The optical channelizer system 32 includes an optical channelizer 20, for example, the optical channelizer 20 illustrated in Figs.
15 1 and 2 and discussed above, a $m \times n$ dimensional photo detector array 34 as opposed to the $1 \times n$ detector array used with the channelizer 20, illustrated in Fig. 2, and a source of a local oscillator frequency comb, with the frequencies, separated, for example, by 1 GHz. In order to generate multiple signal beams, the signal spectrum is passed through a Bragg cell 34. Such Bragg cells are generally known in the art. An example of a suitable Bragg cell 34 is disclosed
20 in I. C. Chang, "Acousto-optic Devices and Applications," IEEE Trans-Sonics and Ultrasonics, Vol. 50-23, P. 2 (1976). The Bragg cell 26 can be driven to replicate the signal spectrum to generate, for example, 25 signal beams, with each version of the signal spectrum being shifted, for example, by 40 MHz with respect to its predecessor. As shown in Fig. 3, in order to provide

such separation, a periodic chirp signal, for example 1 GHz, generally identified with the reference numeral 38, is used to drive the Bragg cell 36. In order to replicate the signal spectrum 25 with each version of the signal spectrum frequency shifted by, for example, 40 MHz with respect to its predecessor, the period of each chirp signal is selected to be 1/40MHz or 25ns. The 25 signal beams are applied to the optical channelizer 20 and translated unto the m x n detector array 34. As a result, the image of each signal spectrum is imaged onto a different row of the m x n detector array 34 and translated horizontally. An optical amplifier (not shown) may be used to amplify the signal before it has been replicated 25 times by the Bragg cell 36.

Fig. 4 illustrates a system for spatially dividing the local oscillator input beam, for example 25 times. As shown in Fig. 5, a monolithic, optical splitter/amplifier integrated circuit (MOSAIC) may be used to spatially divide the local oscillator signal. The output of the MOSAIC 30, in turn, is applied to the optical channelizer 20. In particular, the resulting images of the local oscillator spectrum are projected onto horizontal rows of the photo detector array 34. With such an arrangement, each photo detector 34 processes a different 40 MHz segment of the signal with identical post detection electronics. The signal frequencies detected by adjacent elements in a particular row differ by 1GHz. Neighboring rows operate on segments that are displaced by 40MHz and so on for each row until the entire 1GHz is spanned. With such an arrangement a number of subchannelizers are formed and operated in parallel.

Alternatively, the signal spectrum can be replicated identically, for example, by being passed through the MOSAIC 40, while the local oscillator beam is passed through the Bragg cell 36 to generate frequency shifted versions of the LO spectrum. Since it is desirable to maintain the LO spots centered on their respective detectors, the rows of detectors may have to

be skewed.

Obviously, many modifications and variations of the present invention are possible in light of the above teachings. For example, the invention can be implemented utilizing virtually any type of optical channelizers, such as one based on integrated optical arrayed waveguide gratings. Thus, it is to be understood that, within the scope of the appended claims, the invention may be practiced otherwise than as specifically described above.

What is claimed and desired to be secured by Letters Patent of the United States is:

CLAIMS:

1 1. An optical channelizer system for dividing up a relatively wide bandwidth optical
 2 signal into a plurality of subchannels, the optical channelizer system comprising:
 3 an optical local oscillator (LO) for providing a comb of LO optical frequencies,
 4 an optical splitter for spatially dividing said comb of LO optical frequencies into a
 5 plurality of LO signals;
 6 a device for providing a plurality of replicated versions of the optical signal, each
 7 version being translated by a predetermined frequency;
 8 an optical channelizer for receiving said replicated optical signals and said plurality
 9 of LO signals; and
 10 a photo detector array disposed adjacent said optical channelizer for receiving the
 11 images of said replicated optical signals and said LO signals.

1 2. The optical channelizer system as recited in claim 1, wherein said optical
 2 channelizer is based upon a diffraction grating.

1 3. The optical channelizer system as recited in claim 1, wherein said optical
 2 channelizer is based upon an integrated optical array wave guide grating.

1 4. The optical channelizer system as recited in claim 1, further including an optical
 2 amplifier for amplifying said LO optical signals.

1 5. The optical channelizer system as recited in claim 4, wherein said optical splitter
 2 and optical amplifier is formed from a monolithic optical splitter/amplifier integrated circuit
 3 (MOSAIC).

1 6. The optical channelizer as recited in claim 1, wherein said device for providing a
2 plurality of replicated optical signals is a Bragg cell.

1 7. An optical channelizer system for dividing up a relatively wide bandwidth optical
2 signal into a plurality of subchannels, the optical channelizer comprising;

3 an optical local oscillator (LO) for providing a comb of LO optical frequencies
4 defining LO signals;

5 a device for providing a plurality of replicated LO signals; each replicated signal
6 being translated by a predetermined frequency;

7 an optical splitter for spatially separating said optical signals;

8 an optical channelizer for receiving said plurality of replicated signals from said
9 device and said optical splitter;

10 a photo detector disposed adjacent said optical channelizer for receiving the images
11 of said optical and LO signals.

1 8. The optical channelizer system as recited in claim 7, further including an optical
2 amplifier for amplifying said optical signals.

1 9. The optical channelizer system as recited in claim 7, further including an optical
2 amplifier and wherein said optical splitter and optical amplifier are formed from a
3 monolithic optical splitter/amplifier integrated circuit (MOSAIC).

1 10. The optical channelizer as recited in claim 7, wherein said device for providing a
2 plurality of replicated LO signals is a Bragg cell.

1 11. An optical channelizer system for separating relatively wideband optical signals
2 into a plurality of sub-channels comprising:

3 a plurality of optical sub-channelizers each subchannelizer including means for
4 spatially splitting one or the other of said optical signals or said LO signals;

5 means for replicating and frequency shifting the other of said optical signal or said
6 LO signals;

7 an optical channelizer for receiving signals from said splitting means and said
8 replicating means; and

9 a photo detector array for receiving the images of said signals from said optical
10 channelizer.

1 12. The optical channelizer system as recited in claim 11, wherein said optical
2 channelizer includes a diffraction grating.

1 13. The optical channelizer system as recited in claim 11, wherein said replicating
2 means includes a Bragg cell.

1 14. The optical channelizer system as recited in claim 11, further including an
2 optical amplifier.

1 15. The optical channelizer system as recited in claim 14, wherein said optical
2 amplifier and said splitting means are formed from monolithic optical splitter/optical
3 amplifier integrated circuit (MOSAIC).

HYBRID COHERENT-OPTICAL, RF SIGNAL CHANNELIZER**ABSTRACT**

An optical channelizer system that is adapted to provide instantaneous RF signal channelization at frequencies on the order of 100 GHz or more into channels having bandwidth
5 as small as a few megahertz. In order to improve the channel resolution the optical channelizer system is formed from a plurality of parallel sub-channelizers, for example, twenty-five parallel sub channelizers which can provide 1 GHz channel spacing and 40 MHz signal resolution.




Fig. 1




Fig. 2




Fig. 3




Fig. 4




Fig. 5

No

Docket No. 11-1045

I hereby claim the benefit under Title 35, United States Code, §120 of any United States application(s) listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States application in the manner provided by the first paragraph of Title 35, United States Code, §112, I acknowledge the duty to disclose material information as defined in Title 37, Code of Federal Regulations, §1.56(a) which occurred between the filing date of the prior application and the national or PCT international filing date of this application:

<u>NONE</u> (Number)	<u> </u> (Country)	<u> </u> (Day/Mo./Yr. Filed)	<u> </u> (Status)
-------------------------	--	--	---

I hereby appoint as principal attorneys:

Robert W. Keller, Reg. No. 25,347
Michael S. Yatsko, Reg. No. 28,135
Connie M. Thousand, Reg. No. 43,191
John S. Paniaguas, Reg. No. 31,051

each with full power to prosecute this application, to transact all business in the United States Patent and Trademark Office connected therewith, and to appoint and revoke associate and substitute associate attorneys.

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

Address all telephone calls to: (310) 812-4910

Address all correspondence to: PATENT COUNSEL
TRW Inc.
Space & Electronics Group
One Space Park, E2/6072
Redondo Beach, California 90278

Full name of sole or first inventor Richard L. Davis

Inventor's signature Richard L. Davis Date: 2-17-00

Residence Redondo Beach, California

Citizenship United States

Post Office Address 502 Judy Drive, Redondo Beach, CA 90277